




240W AC/DC 3Ø Input Ultra Slim Industrial DIN Rail Power **XTR-240** series



(XTR-240-xx)



(XTR-240-xxLA)



(XTR-240-xxPI)




































































































































































































































































































































































240W AC/DC 3Ø Input Ultra Slim Industrial DIN Rail Power **XTR-240** series


SPECIFICATION		XTR-240○-12□	XTR-240○-24□	XTR-240○-36□	XTR-240○-48□
		○ =Blank, P □ =Blank, LA, PI			
OUTPUT					
DC VOLTAGE		12V	24V	36V	48V
RATED CURRENT		15A	10A	6.66A	5A
CURRENT RANGE		0 ~ 15A	0 ~ 10A	0 ~ 6.66A	0 ~ 5A
RATED POWER		180W	240W	239.8W	240W
PEAK	CURRENT(5 sec.)	22.5A	15A	10A	7.5A
	POWER(5 sec.)	270W	360W	360W	360W
RIPPLE & NOISE (max.)		Note.2 100mVp-p	100mVp-p	120mVp-p	120mVp-p
VOLTAGE ADJ. RANGE		12 ~ 15V	24 ~ 29V	36 ~ 42V	48 ~ 55V
VOLTAGE TOLERANCE		Note.3 ±1.0%	±1.0%	±1.0%	±1.0%
LINE REGULATION		±0.5%	±0.5%	±0.5%	±0.5%
LOAD REGULATION		±1.0%	±1.0%	±1.0%	±1.0%
SETUP, RISE TIME		2000ms, 60ms/400Vac 1500ms, 60ms/500Vac at full load			
HOLD UP TIME (Typ.)		20ms / 400Vac 40ms / 500Vac at full load			
INPUT					
VOLTAGE RANGE		Note.4 Three-Phase 320 ~ 600Vac 450 ~ 800Vdc (Dual phase operation possible in connecting L1,L3,FG or L2,L3,FG)			
NO LOAD POWER CONSUMPTION (Typ.)		2.5W/400Vac	2.5W/400Vac	2.5W/400Vac	2.5W/400Vac
FREQUENCY RANGE		47 ~ 63Hz			
POWER FACTOR (Typ.)		PF ≥ 0.53/400Vac PF ≥ 0.52/500Vac at full load			
EFFICIENCY (Typ.)		88.7%	92.5%	92.5%	93.5%
AC CURRENT (Typ.)		0.69A/400Vac 0.6A/500Vac			
INRUSH CURRENT (Typ.)		COLD START 10A/400Vac			
LEAKAGE CURRENT		<2mA / 530Vac			
PROTECTION					
OVERLOAD		105%~150% rated output power for more than 5 sec then constant current limiting without shutdown at rate current when Vo=30%~100%			
OVER VOLTAGE		15 ~ 18V	30 ~ 36V	45 ~ 54V	56 ~ 65V
		Hiccup mode , recovers automatically after fault condition is removed			
OVER TEMPERATURE		Shut down o/p voltage or hiccup mode, recovers automatically after temperature goes down			
FUNCTION					
PARALLEL(Optional)		Up to 960W (3+1), please refer to Function Manual for more details			
DC OK RELAY CONTACT		Relay Contact Ratings (max.):30Vdc/1A, 30Vac/0.5A resistive load			
ENVIRONMENT					
WORKING TEMP.		Note.5 -40 ~ +85℃ (Refer to "Derating Curve")			
WORKING HUMIDITY		20 ~ 95% RH non-condensing			
STORAGE TEMP., HUMIDITY		-40 ~ +85℃, 10 ~ 95% RH non-condensing			
TEMP. COEFFICIENT		±0.03%/℃ (0 ~ 60℃)			
VIBRATION		Component:10 ~ 500Hz, 2G 10min./1cycle, 60min. each along X, Y, Z axes; Mounting: Compliance to IEC60068-2-6			





240W AC/DC 3Ø Input Ultra Slim Industrial DIN Rail Power **XTR-240** series

SPECIFICATION		XTR-240○-12□	XTR-240○-24□	XTR-240○-36□	XTR-240○-48□		
		○ =Blank, P □ =Blank, LA, PI					
SAFETY & EMC		Note.7					
SAFETY STANDARDS		UL121201/CSA C22.2 NO.213.17 Class I, Div. 2 Group A, B, C, D Hazardous Locations T4; UL/CUL 61010-1/-2-201; TUV BS EN/EN 62368-1, BS EN IEC/EN IEC 61558-1/-2-16, BS EN/EN 61010-1/-2-201; CB IEC 62368-1, IEC 61558-1/2-16, IEC 61010-1/-2-201; RCM AS/NZS 62368-1,AS/NZS 61558-1/-2-16; BSMI CNS15598-1;CCC GB4943.1;EAC TPTC004 approved; Marine DNV KC KC62368-1 and BIS IS13252 (Part 1):2010 certified, no stock ,contact sale for inquiries					
OVER VOLTAGE CATEGORY		Note.6					
		IEC/EN 61558-1/-2-16 (OVC III, altitude up to 2000m) IEC/EN/UL 61010 (OVC II, altitude up to 5000m) IEC/EN 62368-1 (OVC II, altitude up to 5000m)					
SAFETY EXTRA-LOW VOLTAGE(SELV)		IEC/EN 61558-2-16 (SELV 12V/24V) IEC/EN/UL 61010-2-201 (SELV 12V/24V) IEC/EN 62368-1 (SELV/ ES1 12V/24V)					
WITHSTAND VOLTAGE		I/P-O/P:4.87KVac I/P-FG:2.5KVac O/P-FG:0.5KVac O/P-DC OK:0.5KVac					
ISOLATION RESISTANCE		I/P-O/P, I/P-FG, O/P-FG:>100M Ohms / 500VDC / 25℃ / 70% RH					
EMC EMISSION		Parameter		Standard		Test Level / Note	
		Conducted		BS EN/EN55032(CISPR32) / BS EN/EN61204-3 / CNS15936		Class B	
		Radiated		BS EN/EN55032(CISPR32) / BS EN/EN61204-3 / CNS15936		Class B	
		Harmonic Current		BS EN/EN61000-3-2		Class A	
		Voltage Flicker		BS EN/EN61000-3-3		-----	
EMC IMMUNITY		BS EN/EN55035 , BS EN/EN61204-3 , BS EN/EN61000-6-2:2005 , BS EN/EN IEC61000-6-2:2019					
		Parameter		Standard		Test Level / Note	
		ESD		BS EN/EN61000-4-2		Level 4, 15KV air ; Level 4, 8KV contact	
		Radiated Field		BS EN/EN61000-4-3		Level 3, 10V/m ; criteria A	
		EFT / Burst		BS EN/EN61000-4-4		Level 4, 4KV ; criteria A	
		Surge		BS EN/EN61000-4-5		Level 4, 2KV / Line-Line, Level 4, 4KV/ Line-Earth	
		Conducted		BS EN/EN61000-4-6		Level 3, 10V/m ; criteria A	
		Magnetic Field		BS EN/EN61000-4-8		Level 4, 30A/m ; criteria A	
		Voltage Dips and Interruptions		BS EN/EN61000-4-11		>95% dip 0.5 periods, 30% dip 25 periods> 95% interruptions 250 periods	
OTHERS							
MTBF		1432.3K hrs min. Telcordia SR-332(Bellcore) ;		191.5K hrs min. MIL-HDBK-217F (25℃)			
DIMENSION		48*125.2*125mm (W*H*D)					
PACKING		990g ; 12pcs/12.9Kg/1.16CUFT					
NOTE							
1. All parameters NOT specially mentioned are measured at 400Vac input, rated load and 25℃ of ambient temperature.							
2. Ripple & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1 μ F & 47 μ F parallel capacitor.							
3. Tolerance : includes set up tolerance, line regulation and load regulation.							
4. Dual phase operation is allowed under certain derating to output load. Please refer to derating curves for details.							
5. Installation clearances : 40mm on top, 20mm on the bottom, 5mm on the left and right side are recommended when loaded permanently with full power. In case the adjacent device is a heat source, 15mm clearance is recommended.							
6. The ambient temperature derating of 3.5℃/1000m with fanless models and of 5℃/1000m with fan models for operating altitude higher than 2000m(6500ft).							
7. The power supply is considered as an independent unit, but the final equipment still need to re-confirm that the whole system complies with the EMC directives. For guidance on how to perform these EMC tests, please refer to “EMI testing of component power supplies.” (as available on https://www.meanwell.com/Upload/PDF/EMI_statement_en.pdf)							
※ Product Liability Disclaimer : For detailed information, please refer to https://www.meanwell.com/serviceDisclaimer.aspx							

■ Block Diagram




■ Derating Curve



Note : Dual phase operating temperature is between -30°C~+85°C.

■ Output derating VS input voltage



Note : When ambient temperature is between -30°C~-10°C and unit is operated in dual-phase input mode :
 - At dual-phase input 320~380Vac, power supply can be loaded but might experience hiccup at cold start for 5~10 seconds.

■ Peak Power

$$P_{av} = \frac{P_{pk} \times t + P_{npk} \times (T-t)}{T} \leq P_{rated}$$

$$\text{Duty} = \frac{t}{T} \times 100\% \leq 35\%$$

$$t \leq 5 \text{ sec}$$

P_{av} : Average output power (W)


P_{pk} : Peak output power (W)

P_{npk} : Non-peak output power (W)


P_{rated} : Rated output power (W)

t : Peak power width (sec)

T : Period (sec)



— 3Ø 320 ~ 600Vac



Peak output power (W)

For example (24V model) :

$V_{in} = 400V$ $\text{Duty}_{max} = 10\%$

$P_{av} = P_{rated} = 240W$

$P_{pk} = 360W$

$t \leq 5 \text{ sec}$

$T \geq \frac{5 \text{ sec}}{10\%} \geq 50 \text{ sec}$

$$P_{npk} \leq \frac{T P_{av} - t P_{pk}}{T-t}$$



$P_{npk} \leq 226W$



240W AC/DC 3Ø Input Ultra Slim Industrial DIN Rail Power **XTR-240** series

■ Function Manual


Pin No.	Function	Description
1,2	DC OK	Contact close : PSU turns ON/DC_OK ; Contact open : PSU turns OFF/DC_fail; Contact ratings (max.): 30Vdc/1A ,30Vac/0.5A resistive load.
3	P+ (By request)	Current sharing signal. When units are connected in parallel, the P+ pins of the units should be connected mutually to allow current balance between units.
4	P- (By request)	Current sharing signal. When units are connected in parallel, the P- pins of the units should be connected mutually to allow current balance between units. P- Signal is internally connected to -Vo.



1.Parallel Use (By request)

XTR-240 has the built-in active current sharing function and can be connected in parallel, up to 4 units, to provide higher output power as exhibited below :



- (1) Parallel operation is available by connecting the units shown as below (P+,P- are connected mutually in parallel).
- (2) Difference of output voltages among parallel units should be less than 0.2V.
- (3) The total output current must not exceed the value determined by the following equation (Output current at parallel operation)=(The rated current per unit) x (Number of unit) x 0.9.
- (4) In parallel operation 4 units is the maximum, please consult the manufacture for other applications.
- (5) The power supplies should be paralleled using short and large diameter wiring and then connected to the load.
- (6) When in parallel operation, the minimum output load should be greater than 5% of total output load. (Min. load >5% rated current per unit x number of unit)
- (7) P+ and P- lines should be twisted in pairs



※ Please contact MEAN WELL for more details.

2.DC OK Relay Contact

Contact Close	PSU turns ON / DC OK.
Contact Open	PSU turns OFF / DC Fail.
Contact ratings (max.)	30Vdc/1A ,30Vac/0.5A resistive load.




External voltage source (U) and resistor (R)
(The max. Sink is 30Vdc/1A,30Vac/0.5A)

Internal circuit of DC_OK, via relay contact

3. Protection Against Inverse Reverse From The Load (By request)

Prevent PSU damage from Back Electro magnetic Force during deceleration of motor or inductive load.




PSU'S ORing FET turn OFF voltage	
MODEL	Max. allowable reverse voltage
XTR-240-12	<16V
XTR-240-24	<35V
XTR-240-36	<50V
XTR-240-48	<63V

■ Mechanical Specification

(Unit:mm , Tolerance ± 1 mm)

Case No. 303



■ Recommend Wiring


※ Screw Terminal Torque

		AC Input T.B	DC Output T.B	Signal connector
Solid Wire		6mm ² max.	6mm ² max.	1.5mm ² max.
A.W.G	XTR-240-12	18~10 AWG	12~10 AWG	24~16 AWG
	XTR-240-24/36/48		16~10 AWG	
Wire Stripping Length		10~11mm	10~11mm	8~9mm
Screw Terminal Torque		5 Lb-In	5 Lb-In	/

※ Lever-Actuated and Push In

		AC Input T.B	DC Output T.B	Signal connector
Solid Wire		6mm ² max.	6mm ² max.	1.5mm ² max.
A.W.G	XTR-240-12	18~10 AWG	12~10 AWG	24~16 AWG
	XTR-240-24/36/48		16~10 AWG	
Wire Stripping Length		10~11mm	10~11mm	8~9mm
Screw Terminal Torque		Not applicable		

■ Installation Instruction



This series fits DIN rail TS35/7.5 or TS35/15.
For installation details, please refer to the Instruction manual.

ADMISSIBLE DIN-RAIL: TS35/7.5 OR TS35/15
(For reference only. Not included with unit.)

■ Installation Manual

Please refer to : <http://www.meanwell.com/manual.html>

 www.simpex.ch

Besuchen Sie unseren Simpex E-Shop
mit über 12'000 Produkten.

Er bietet Ihnen eine breite Funktionsvielfalt, sowie intelligente
Suchfunktionen. Ob Sie den Shop als Einkaufsplattform oder als
Produktfinder nutzen – im Simpex E-Shop haben Sie alle Infor-
mationen schnell und tagesaktuell zur Hand.

24h und das 365 Tage im Jahr.



Hauptsitz

Simpex Electronic AG
Binzackerstrasse 33
CH-8620 Wetzikon
Telefon +41 44 931 10 10
E-Mail contact@simpex.ch
Internet www.simpex.ch

Manufaktur

Simpex Electronic SA
En Bas-le-Port 1
CH-2088 Cressier
E-Mail contact@simpex.ch
Internet www.simpex.ch